XYCOM AUTOMATION™

OPERATOR INTERFACE PRODUCTS APPLICATION NOTE

Subject: Copy D-Script from one project to another.   AN# 1111
Date: 8-23-02
Name: Allen Heskett
Page: 1 of 2.

Description: Copy D-Script from one project to another.

Affected Products: GP, GLC, and LogiTouch Series Products.

Problem:

1. Make a new Project like you normally would.

2. Next go to the "Project Manager Screen" and then go to the menu "Project".

3. Then "Change Project Manager". This will change your "Project Manager" screen / layout to look like figure 1.

4. Now you can expand, hit the "+" sign next to the Project name that you want to copy the screen from. In figure 1 the Project called "Calculator" is expanded and you can see several more files. Highlight the "Base Files" and go to the "B1" screen (or the screen you want to copy) and "Copy" (the copy is in the "Edit" pull down menu).

5. Next go to the new project and do the same thing of expanding, then do a "Paste". Now this will paste the screen (example is B1) into the new project. If you already have a "B1" screen, it will ask you if you want to write over the current "B1" screen. Just enter yes.

6. When you paste a screen, you are pasting the D-Script for that screen too.

7. Notes: Ctrl C and Ctrl V short cuts can be also used for coping and pasting.

Copying Global D-Script from one project to another.

1. Open up the project that has the Global D-Script in which you want to copy from.

2. Go to the "Special" menu and go to "Global D-Script". Pick the D-Script that you want to copy.

3. Hit the "Copy" button.

4. Next close out all of the screens and go back to your "Project Manager".

5. Open the new project that you want to paste the D-Script too.

6. Again go to the "Special" menu and go to "Global D-Script".

7. Go to the "Special" menu and go to "Global D-Script". Opening you may have one or several D-Scripts listed. Then hit the paste button. Then you should be able to see that the pasted D-Script will be there.

Figure